

Multipurpose button

by MClimate



 Battery included

Description

MClimate Multipurpose Button LoRaWAN® is a simple device with many applications. Featuring a single button with 3 types of clicks and a temperature sensor, only your imagination limits what happens when the customer presses the button.

SKU: MC-LW-BTN-01

Product features

- Button with 3 click types (single, double and triple)
- Temperature sensor
- Ultra-low power consumption

Applications

- Smart Buildings
- Smart home
- Residential buildings
- Commercial buildings

Device specifications

Mechanical specifications

WEIGHT EXCL. BATTERY 26gr

DIMENSIONS 71x41x18mm

ENCLOSURE ABS

Operating conditions

TEMPERATURE 0 - +50°C

HUMIDITY 0-80% RH (non-condensing)

Power supply

BATTERY TYPE ER10280 (included in the device)

OPERATING VOLTAGE 3VDC

EXPECTED BATTERY LIFE < 10 years (depending on configuration and environment)

Radio/Wireless

WIRELESS TECHNOLOGY	LoRaWAN® 1.0.3
WIRELESS SECURITY	LoRaWAN® End-to-End encryption (AES-CTR)
LORAWAN DEVICE TYPE	Class A End-device
SUPPORTED LORAWAN FEATURES	OTAA, ADR, Adaptive Channels setup
SUPPORTED LORAWAN REGIONS	EU863 – 870; Other LoRaWAN regional settings available upon request
LINK BUDGET	130dB
RF TRANSMIT POWER	14dB

Data types

KEEPALIVE	TYPE	VALUE	VALUE NAME	DATA SIZE	NOTES
	0x00		Reason to send message	1	Possible reasons: Keepalive; Button press
	0x01		Battery voltage	1	
	0x02		Temperature	2	
	0x04		Button press type - single, double or triple press	1	

LIST OF FUNCTIONS FROM THE PROTOCOL DOCUMENTATION

Read/Write up-link messages types
 Read/Write keepalive period
 Read/Write communication watch-dog parameters
 Read device firmware and hardware version
 Read/Write network join-retry period

Sensors

Temperature

RESOLUTION	0,1°C
ACCURACY	±0,5°C

